

DATA TRANSMISSION METHOD AND APPARATUS IN RELAY TRANSMISSION TYPE RADIO NETWORK

BACKGROUND OF THE INVENTION

Field of the invention

5 The present invention relates to a data transmission method and an apparatus therefor in a relay transmission type radio network.

Description of the Related Art

FIG. 18 is a diagram illustrating a cell configuration of
10 a conventional cellular system. As for the cell configuration of this cellular system, it is comprised of cells 101 and base stations (nodes) 102, where a serviceable area is constituted by placing a plurality of cells as in FIG. 18. Each of nodes 102 is connected by a wire basic network 104 and a wire circuit
15 103, so that service signals such as voice and data and various control signals are communicated via these links. Moreover, there are cases where each of nodes 102 is connected to the wire basic network 104 by providing concentration stations or the like hierarchically between them. A terminal station 105
20 performs communication with the node 102, and transmits and receives various signals communicated by the wire basic network 104 and the wire circuit 103. The wire basic network 104 has a server apparatus installed for managing location information on the terminals and radio nodes, and performing accounting and
25 so on.

In order to cope with the increase in the number of subscribers to the cellular systems such as portable telephones and the Fixed Wireless Access, a technique of reducing a cell radius to decrease a processing load per node is adopted. In
5 the case of constructing the system with such minimal cells, a very large number of the nodes are placed so as to secure a service area.

In addition, in the case where a high density data transmission system such as multilevel modulation is applied
10 in order to sup-linkport high-speed data transmission, the area covered by one node inevitably becomes smaller to secure required received quality, and so a very large number of the nodes are also placed in this case.

Furthermore, while the cellular systems were mainly
15 designed in quasi-micro and microwave zones in the past, construction of the cellular systems using quasi-millimeter and millimeter wave zones is expected because of a crisis of frequency pressure. A higher frequency weakens a diffraction effect and makes it markedly straight so that an unexpected call becomes
20 difficult, which inevitably leads to a smaller area covered by each node. To be more specific, a very large number of the nodes are also placed in such a case since a call area must be secured with the minimal cells.

In the case of constructing the systems with a large number
25 of the minimal cells, it is essential to consolidate a wire network for the purpose of connecting the node group-link to the basic network. To connect a very large number of the geographically unevenly distributed nodes with the basic network, however, it

is necessary to install the wire networks everywhere and so the cost of the entire system increases. Therefore, there is a technique of connecting the nodes by radio and performing relay transmission so as to expand the service area.

5 FIG. 19 is a diagram illustrating an example of the cell configuration wherein relay nodes 204, 205 and 206 are placed around a core node 203 connected to a wire network 201 by a wire circuit 202 and the relay nodes and the core node are connected by radio. A symbol 208 indicates an example of an area covered
10 by the node. The up-link packet transmitted from a terminal 207 reaches the core node 203 via the relay nodes 205 and 204, and then the packet received by the core node 203 is communicated to the wire network 201 by way of the wire circuit 202. On the other hand, the down-link packet to the terminal 207 sent from
15 the wire network 201 is sent to the core node 203 first by way of the wire circuit 202 and then is communicated from the core node 203 to the terminal 207 by way of the relay nodes 204 and 205.

In the case of transmitting the down-link packet in the
20 cell configuration shown in FIG. 19, there was a challenge that the appropriate relay route must be selected out of a plurality of the relay routes according to the location of the terminal 207, and that, if the terminal station moves, the relay route of the down-link packet to the terminal station must be changed
25 as appropriate following the move.

SUMMARY OF THE INVENTION

Thus, an object of the present invention is to provide the data transmission method and apparatus in a relay transmission

type radio network capable of selecting the appropriate down-link relay route according to the location of the terminal station.

Another object of the present invention is to provide the data transmission method and apparatus in the relay transmission
5 type radio network allowing the down-link relay route to be changed following the move of the terminal station and capable of selecting the down-link relay route appropriate to the above described move.

According to the first aspect of the present invention,
10 a data transmission method in a relay transmission type radio network including a core node connected to a wire network, relay nodes relaying a down-link packet transmitted from said core node and an up-link packet directed toward said core node and a terminal station capable of transmission and reception of packet
15 with both of said core node and said relay node, comprising:
a registration step for registering with a relay node list held by the node, as a pair, ID information on said terminal station and a relay source node included in the up-link packet transmitted by said terminal station, in each of said core node
20 and said relay node; and

a selection step for selecting a down-link relay route of the down-link packet addressed to said terminal station on the basis of said relay node list, in each of said core node and said relay node.

25 According to the second aspect of the present invention, a relay node relaying a down-link packet transmitted from a core node connected to a wire network and an up-link packet directed towards said core node, and capable of communication with a terminal

station, comprising a relay node list for having recorded ID information on said terminal station and a relay source node included in the up-link packet directed toward said core node by said terminal station and giving a down-link relay route of the down-link packet addressed to said terminal station on the basis of said ID information.

According to the third aspect of the present invention, a core node connected to a wire network, and capable of transmission and reception of packet with both of a terminal station and a relay node, comprising a relay node list for having recorded ID information on said terminal station and the relay node that is a relay source node included in a received up-link packet and giving a down-link relay route of a down-link packet addressed to said terminal station on the basis of said ID information is provided.

According to the fourth aspect of the present invention, a terminal station capable of transmission and reception of packet with both of a core node connected to a wire network and a relay node relaying a down-link packet transmitted from said core node and an up-link packet directed toward said core node, setting ID information on a source terminal station registered with a relay node list of said core node or said relay node as a pair with ID information on a relay source node on said up-link packet and transmitting said up-link packet to a relay destination node.

In the data transmission method according to the present invention, each of the core node and the relay nodes has the relay node list for giving the down-link relay route of the down-link packet addressed to the terminal station, and selects

the appropriate down-link relay route for the down-link packet addressed to the terminal station according to the location of the terminal station on the basis of the relay node list.

The relay node according to the present invention holds
5 as the relay node list the ID information on the terminal station and the relay source node included in the up-link packet directed toward the core node by the terminal station and selects the appropriate down-link relay route for the down-link packet addressed to the terminal station on the basis of information
10 on the up-link relay route according to the ID information of the relay node list.

The core node according to the present invention holds as the relay node list the ID information on the terminal station and the relay source node included in the up-link packet
15 transmitted by the terminal station and received by way of the relay destination node, and selects the appropriate down-link relay route for the down-link packet addressed to the terminal station on the basis of information on the up-link relay route according to the ID information of the relay node list.

20 The terminal station according to the present invention transmits to the relay destination node the up-link packet including the ID information on the source terminal station registered with the relay node list of the core node or the relay node as a pair with an ID number of the relay source node. Thus,
25 it becomes possible, in each of the core node and the relay nodes, to generate the relay node list used to select the down-link relay route of the down-link packet addressed to the terminal

station, and thus selection of the appropriate down-link relay route for the down-link packet is implemented.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic diagram showing how a terminal station
5 having received a broadcast packet sends back an up-link ACK packet in a data transmission method according to an embodiment of the present invention;

FIG. 2 is a schematic diagram showing a field configuration of the broadcast packet in the data transmission method according
10 to the embodiment of the present invention;

FIG. 3 is a schematic diagram showing a configuration of the ACK packet in the data transmission method according to the embodiment of the present invention;

FIG. 4 is a flowchart showing an up-link ACK packet procedure
15 performed on each relay node and core node in the data transmission method according to the embodiment of the present invention;

FIG. 5 is a diagram illustrating an example of the relay node list held by the relay node in the data transmission method according to the embodiment of the present invention;

FIG. 6 is a diagram illustrating how the relay node list
20 is generated according to the embodiment of the present invention;

FIG. 7 is a diagram illustrating the relay node list generated by the relay node list generation procedure according to the embodiment of the present invention;

FIG. 8 is a diagram illustrating the relay node list generated
25 by the relay node list generation procedure according to the embodiment of the present invention;

FIG. 9 is a diagram illustrating the relay node list generated by the relay node list generation procedure according to the embodiment of the present invention;

FIG. 10 is a diagram showing how the relay node list is generated in the case where the terminal station has moved in the data transmission method according to the embodiment of the present invention;

FIG. 11 is a diagram illustrating the relay node list that is generated on the relay node in the case where the terminal station has moved in the data transmission method according to the embodiment of the present invention;

FIG. 12 is a flowchart showing another example of the up-link ACK packet procedure performed on each relay node and core node in the data transmission method according to the embodiment of the present invention;

FIG. 13 is a diagram concretely illustrating how the relay node list is generated in the data transmission method according to the embodiment of the present invention;

FIG. 14 is a schematic diagram showing a configuration of an up-link packet in the data transmission method according to the embodiment of the present invention;

FIG. 15 is a schematic diagram showing a configuration of a down-link packet in the data transmission method according to the embodiment of the present invention;

FIG. 16 is a flowchart showing the relay and transmission process of the down-link packet in the data transmission method according to the embodiment of the present invention;

FIG. 17 is a diagram concretely illustrating the down-link packet relay operation in the data transmission method according to the embodiment of the present invention;

FIG. 18 is a diagram illustrating a cell configuration of
5 a conventional cellular system; and

FIG. 19 is a diagram illustrating an example of a cell configuration of a radio relay type cellular system.

DESCRIPTION OF THE PREFERRED EMBODIMENT

An embodiment of the present invention will be described
10 hereafter.

First, selection of a down-link relay route in this embodiment will be described by using FIGS. 1, 2, 3 and 4. In this embodiment, a case where a relay destination node (receiver side relay node) for each relay node to relay and transmit an
15 up-link packet is already known is assumed. To be more specific, the case where the relay route of the up-link packet is given in advance is assumed. There are the cases where a directional antenna is installed on each relay node and core node. There are the cases where the directional antenna is fixedly installed
20 and where it is adaptably installed as to its directivity. Installing the directional antenna cuts back interference given to surrounding nodes and the terminal station, whereby it becomes possible to achieve high link capacity in the entire system.

Each relay node and core node periodically transmits a
25 broadcast packet, and there are the cases where the broadcast packet is transmitted with fixed transmitting power. Details of the broadcast packet and an up-link ACK packet are described

later by using FIGS. 2 and 3. In FIG. 1, relay nodes F08, F12 and F09 periodically transmit the broadcast packet by way of down-link radio circuits F02, F07 and F10 respectively. Each terminal station receives the broadcast packets from a plurality of nodes, and selects the node having transmitted the broadcast packet of the highest received power or of the best received quality of the received broadcast packets. Terminals F01, F13 and F11 in FIG. 1 select the relay nodes F08, F12 and F09 respectively. The terminals F01, F13 and F11 having selected the above described relay nodes transmit the up-link ACK packets to the relay nodes F08, F12 and F09 respectively. The up-link ACK packets transmitted from the terminals F01, F13 and F11 are communicated to a core node F05 by way of relay routes F03, F06 and F04 respectively.

FIG. 2 is a schematic diagram showing a field configuration of the broadcast packet according to the embodiment of the present invention. The broadcast packet is comprised of a field E02 showing a core node ID, a field E03 showing a relay node ID, a field E04 showing data and an other field E01. In each of the relay nodes, the ID of the core node of a cell to which the relay node belongs is set in the core node ID field E02. On the core node, its own node ID is set in the relay node ID field E03. Moreover, there are cases where the core node ID field E02 is excluded. The other field E01 has a pilot signal, a packet ID and the like set therein. There are cases where the order of the fields is changed. There are also the cases where the other field E01 is divided and placed.

FIG. 3 is a schematic diagram showing a configuration of the up-link ACK packet that is a response signal in the case where the terminal station according to the embodiment of the present invention receives the broadcast packet. The up-link
5 ACK packet is comprised of a field G02 showing a relay destination node (receiver side relay node) ID, a field G03 showing a relay source node (sender side relay node) ID, a field G04 showing a source terminal station ID, and an other field G01. Each of the relay nodes sets an up-link relay destination node ID as
10 the relay destination node ID, sets its own node ID as the relay source node ID, and sets the ID of the terminal station having transmitted the up-link ACK packet as the source terminal station ID. In the case where each of the terminal stations sends the up-link ACK packet, the terminal station sets the information
15 indicating that it has transmitted in the relay source node ID field G03. It is also possible to simultaneously set a plurality of the relay destination node IDs in the relay destination node ID field G02. The other field G01 has a pilot, an up-link and down-link link indicator, a packet ID, data and the like set
20 therein. The order of the fields may change. The other field G01 may be divided and placed.

FIG. 4 shows an up-link ACK packet procedure performed on each relay node and the core node of the embodiment of the present invention. Each node detects arrival of the up-link ACK packet
25 in a step H01, and it proceeds to a step H02 in the case where the up-link ACK packet is detected, and it returns to the step H01 in the case where the up-link ACK packet is not detected. In the step H02, each node determines whether the received up-link

ACK packet is the packet being relayed or the packet transmitted from the terminal station. Here, the determination is made by referring to the field G03 representing the relay source node included in the up-link ACK packet, and if information set in

5 the field G03 indicates anything other than the relay source node, each node determines that the received up-link ACK packet is the packet from the terminal station. In the case where it is determined to be the up-link ACK packet from the terminal station in the step H02, each node transmits the up-link ACK

10 packet to the relay destination node after setting necessary information such as the relay source node ID in a step H05. In the case where the terminal station or the relay node transmits the up-link ACK packet, it may control the transmitting power of the up-link ACK packet so as to meet predetermined received

15 power or predetermined received quality at a transmission destination node. It is possible to cut back the interference and increase the link capacity by controlling the transmitting power of the up-link ACK packet. In the case where it is determined to be the up-link ACK packet from the relay source node in the

20 step H02, each node refers to the relay destination node ID included in the up-link ACK packet in a step H03, and it proceeds to a step H04 if its own node ID is set in the field G02, or returns to the step H01 if anything other than its own node ID is set in the field G02. In the step H04, each node obtains

25 the information on the relay source node ID and the source terminal station ID included in the received up-link ACK packet, and records their relationship on a relay node list. In the case where the above described source terminal station ID is already registered

with the relay node list, each node cancels the registration and then registers the relay source node ID and the source terminal station ID of this time. If there is no change in the relationship between the relay source node ID and the source terminal station ID, however, neither of them needs to be registered. Details of the relay node list will be described later by referring to FIG. 5. After registering it with the relay node list, each node transmits the up-link ACK packet to the relay destination node after setting necessary information such as the relay source node ID in the step H05.

FIG. 5 is a diagram illustrating an example of the relay node list held by the relay node according to the embodiment of the present invention. In FIG. 5, it describes the relationship between the node ID showing a relay destination node of a down link and a destination terminal station ID showing the terminal station receiving a down-link packet. For instance, in the case where a terminal station MS-3 is specified as the destination terminal station of a certain down-link packet, the relay node holding the relay node list of FIG. 5 transmits the received down-link packet to a relay node BS-C. In the case where the node ID for the terminal station is not registered on the relay node list on the relay node or the core node, it is regarded as the down-link packet sent to the terminal station. When registering a pair of new node ID and terminal station ID on the relay node list, in the case where the terminal station ID is already registered, the registration is canceled and then the pair of the new node ID and terminal station ID are registered. However, in the case where, as a result of making an inquiry

about the relationship between the node ID and the terminal station registered on the relay node list, the same pair as the new node ID and terminal station ID are already registered, neither ID needs to be registered. In the case where the pair of the node
5 ID and the terminal station ID on the relay node list is not up-link dated or inquired about for a fixed time or longer, the registration of the pair may be deleted.

FIG. 6 is a diagram illustrating how the relay node list according to the embodiment of the present invention is generated.

10 It is assumed that the up-link relay destination node is already known. In FIG. 6, relay nodes RN-1, RN-2, RN-3 and RN-4 are periodically transmitting the broadcast packet respectively.

A terminal station MS-A receives the broadcast packet by way of a radio propagation path I01, and selects the relay node
15 RN-1 as a connection node. The terminal station MS-A transmits the up-link ACK packet to the relay node RN-1 by way of a radio propagation path I04. At this time, the up-link ACK packet has the ID "MS-A" set as the source terminal station ID and the ID "RN-1" set as the relay destination node ID respectively. The relay
20 node RN-1 receives the up-link ACK packet transmitted from the terminal station MS-A, and then transmits the up-link ACK packet to the relay node RN-3 that is the up-link relay destination node by way of a radio propagation path I02. At this time, the up-link ACK packet has the ID "RN-1" set as the relay source
25 node ID, the ID "MS-A" set as the source terminal station ID and the ID "RN-3" set as the relay destination node ID respectively. The relay node RN-3 refers to the relay source node ID "RN-1" and the source terminal station ID "MS-A" included in the up-link

ACK packet transmitted from the relay node RN-1 to register the pair of the node ID "RN-1" and the terminal station ID "MS-A" with the relay node list. The relay node RN-3 transmits the up-link ACK packet received from the relay node RN-1 to the relay
5 node RN-4 that is the up-link relay destination node of the relay node RN-3 by way of a radio propagation path I03. At this time, the up-link ACK packet has the ID "MS-A" set as the source terminal station ID, the ID "RN-3" set as the relay source node ID and the ID "RN-4" set as the relay destination node ID respectively.
10 The relay node RN-4 receives the up-link ACK packet transmitted from the relay node RN-3 by way of the radio propagation path I03, and registers with the relay node list held by the relay node RN-4 the source terminal station ID "MS-A" and the relay source node ID "RN-3" included in the up-link ACK packet as a
15 pair.

In FIG.6, a terminal station MS-B receives the broadcast packet from the relay node RN-2 by way of a radio propagation path I09, and selects the relay node RN-2 as the connection node. The terminal station MS-B transmits the up-link ACK packet to
20 the relay node RN-2 by way of a radio propagation path I08. At this time, the up-link ACK packet has the ID "MS-B" set as the source terminal station ID and the ID "RN-2" set as the relay destination node ID respectively. The relay node RN-2 receives the up-link ACK packet transmitted from the terminal station
25 MS-B, and then transmits the up-link ACK packet to the relay node RN-3 that is the up-link relay destination node for the relay node RN-2 by way of a radio propagation path I05. At this time, the up-link ACK packet has the ID "RN-2" set as the relay

source node ID, the ID "MS-B" set as the source terminal station ID and the ID "RN-3" set as the relay destination node ID respectively. The relay node RN-3 refers to the relay source node ID "RN-2" and the source terminal station ID "MS-B" included
5 in the up-link ACK packet transmitted from the relay node RN-2 to register the pair of the node ID "RN-2" and the terminal station ID "MS-B" with the relay node list held by the relay node RN-3. The relay node RN-3 transmits the up-link ACK packet received from the relay node RN-2 to the relay node RN-4 that is the up-link
10 relay destination node of the relay node RN-3 by way of the radio propagation path I03. At this time, the up-link ACK packet has the ID "MS-B" set as the source terminal station ID, the ID "RN-3" set as the relay source node ID and the ID "RN-4" set as the relay destination node ID respectively. The relay node RN-4
15 receives the up-link ACK packet transmitted from the relay node RN-3 by way of the radio propagation path I03, and registers with the relay node list held by the relay node RN-4 the source terminal station ID "MS-B" and the relay source node ID "RN-3" included in the up-link ACK packet as a pair.

20 In FIG.6, a terminal station MS-D receives the broadcast packet from the relay node RN-5 by way of a radio propagation path I12, and selects the relay node RN-5 as the connection node. The terminal station MS-D transmits the up-link ACK packet to the relay node RN-5 by way of a radio propagation path I11. At
25 this time, the up-link ACK packet has the ID "MS-D" set as the source terminal station ID and the ID "RN-5" set as the relay destination node ID respectively. The relay node RN-5 receives the up-link ACK packet transmitted from the terminal station

MS-D, and then transmits the up-link ACK packet to the relay node RN-2 that is the up-link relay destination node for the relay node RN-5 by way of a radio propagation path I10. At this time, the up-link ACK packet has the ID "RN-5" set as the relay
5 source node ID, the ID "MS-D" set as the source terminal station ID and the ID "RN-2" set as the relay destination node ID respectively.

The relay node RN-2 refers to the relay source node ID "RN-5" and the source terminal station ID "MS-D" included in the up-link
10 ACK packet transmitted from the relay node RN-5 to register the pair of the node ID "RN-5" and the terminal station ID "MS-D" with the relay node list held by the relay node RN-2. The relay node RN-2 transmits the up-link ACK packet received from the relay node RN-5 to the relay node RN-3 that is the up-link relay
15 destination node of the relay node RN-2 by way of the radio propagation path I05. At this time, the up-link ACK packet has the ID "MS-D" set as the source terminal station ID, the ID "RN-2" set as the relay source node ID and the ID "RN-3" set as the relay destination node ID respectively. The relay node RN-3
20 refers to the relay source node ID "RN-2" and the source terminal station ID "MS-D" included in the up-link ACK packet transmitted from the relay node RN-2 to register the pair of the node ID "RN-2" and the terminal station ID "MS-D" with the relay node list held by the relay node RN-3. The relay node RN-3 transmits the up-link
25 ACK packet received from the relay node RN-2 to the relay node RN-4 that is the up-link relay destination node of the relay node RN-3 by way of the radio propagation path I03. At this time, the up-link ACK packet has the ID "MS-D" set as the source

terminal station ID, the ID "RN-3" set as the relay source node ID and the ID "RN-4" set as the relay destination node ID respectively.

5 The relay node RN-4 receives the up-link ACK packet transmitted from the relay node RN-3 by way of the radio propagation path I03, and registers with the relay node list held by the relay node RN-4 the source terminal station ID "MS-D" and the relay source node ID "RN-3" included in the up-link ACK packet as a pair.

10 In FIG.6, a terminal station MS-C receives the broadcast packet from the relay node RN-3 by way of a radio propagation path I06, and selects the relay node RN-3 as the connection node. The terminal station MS-C transmits the up-link ACK packet to the relay node RN-3 by way of a radio propagation path I07. At
15 this time, the up-link ACK packet has the ID "MS-C" set as the source terminal station ID and the ID "RN-3" set as the relay destination node ID respectively. The relay node RN-3 receives the up-link ACK packet transmitted from the terminal station MS-C, and then transmits the up-link ACK packet to the relay
20 node RN-4 that is the up-link relay destination node for the relay node RN-3 by way of the radio propagation path I03. At this time, the up-link ACK packet has the ID "RN-3" set as the relay source node ID, the ID "MS-C" set as the source terminal station ID and the ID "RN-4" set as the relay destination node
25 ID respectively. The relay node RN-4 receives the up-link ACK packet transmitted from the relay node RN-3 by way of the radio propagation path I03, and registers with the relay node list held by the relay node RN-4 the source terminal station ID "MS-C"

and the relay source node ID "RN-3" included in the up-link ACK packet as a pair.

FIG. 7 is a diagram illustrating the relay node list on the relay node RN-2 generated by the relay node list generation procedure described by using FIG. 6. As shown in FIG. 7, the list indicating the down-link relay destination node to relay the down-link packet for each terminal station is generated on the relay node RN-2 shown in FIG. 6, and accordingly, selection of the down-link relay route for each terminal station is autonomously implemented in the relay node RN-2.

FIG. 8 is a diagram illustrating the relay node list on the relay node RN-3 generated by the relay node list generation procedure described by using FIG. 6. As shown in FIG. 8, the list indicating the down-link relay destination node to relay the down-link packet for each terminal station is generated on the relay node RN-3 shown in FIG. 6, and accordingly, selection of the down-link relay route for each terminal station is autonomously implemented in the relay node RN-3.

FIG. 9 is a diagram illustrating the relay node list on the relay node RN-4 generated by the relay node list generation procedure described by using FIG. 6. As shown in FIG. 9, the list indicating the down-link relay destination node to relay the down-link packet for each terminal station is generated on the relay node RN-4 shown in FIG. 6, and accordingly, selection of the down-link relay route for each terminal station is autonomously implemented in the relay node RN-4.

Next, FIG. 10 is a diagram showing how the relay node list is generated in the case where the terminal station MS-A in FIG.

6 has moved. FIG. 10 shows the case where the terminal station MS-A moves from the area covered by the relay node RN-1 to the area covered by the relay node RN-2.

In FIG. 10, the terminal station MS-A receives the broadcast
5 packet from the relay node RN-2 by way of a radio propagation path I14, and selects the relay node RN-2 as the connection node. The terminal station MS-A transmits the up-link ACK packet to the relay node RN-2 by way of a radio propagation path I13. At this time, the up-link ACK packet has the ID "MS-A" set as the
10 source terminal station ID and the ID "RN-2" set as the relay destination node ID respectively. The relay node RN-2 receives the up-link ACK packet transmitted from the terminal station MS-A, and then transmits the up-link ACK packet to the relay node RN-3 that is the up-link relay destination node for the
15 relay node RN-2 by way of the radio propagation path I05. At this time, the up-link ACK packet has the ID "RN-2" set as the relay source node ID, the ID "MS-A" set as the source terminal station ID and the ID "RN-3" set as the relay destination node ID respectively. The relay node RN-3 refers to the relay source
20 node ID "RN-2" and the source terminal station ID "MS-A" included in the up-link ACK packet transmitted from the relay node RN-2 to register the pair of the node ID "RN-2" and the terminal station ID "MS-A" with the relay node list held by the relay node RN-3. Here, while the terminal station MS-A pairing off with the relay
25 node RN-1 is already registered with the relay node list held by the relay node RN-3 as shown in FIG. 8, the terminal station MS-A pairs off with the relay node RN-2 this time, so that the relay node RN-3 changes it by deleting the ID "MS-A" registered

for the ID "RN-1" to newly have the ID "RN-2" and the ID "MS-A" as a pair. The relay node RN-3 transmits the up-link ACK packet received from the relay node RN-2 to the relay node RN-4 that is the up-link relay destination node of the relay node RN-3
5 by way of the radio propagation path I03. At this time, the up-link ACK packet has the ID "MS-A" set as the source terminal station ID, the ID "RN-3" set as the relay source node ID and the ID "RN-4" set as the relay destination node ID respectively. The relay node RN-4 receives the up-link ACK packet transmitted
10 from the relay node RN-3 by way of the radio propagation path I03, and attempts to register with the relay node list held by the relay node RN-4 the source terminal station ID "MS-A" and the relay source node ID "RN-3" included in the up-link ACK packet as a pair. However, the relay node RN-4 does not need to newly
15 register it since the pair of the ID "MS-A" and the ID "RN-3" is already registered with the relay node list held by the relay node RN-4 as shown in FIG. 9.

FIG. 11 shows the relay node list that is generated on the relay node RN-3 in the case where the terminal station MS-A moves
20 from the area covered by the relay node RN-1 to the area covered by the relay node RN-2 as shown in FIG. 10. As shown in FIG. 11, the relay node RN-3 shown in FIG. 10 cancels the registration of the terminal station MS-A pairing off with the relay node RN-1 and registers the ID "MS-A" so that it pairs off with the
25 relay node RN-2. There are cases where cancellation of the terminal station MS-A pairing off with the relay node RN-1 is performed after some time has elapsed. In this case, the two relay routes by way of the relay nodes RN-1 and RN-2 is set to

one terminal station MS-A, which receives the packets from those two relay nodes RN-1 and RN-2 so as to have the effect of site diversity.

As above, according to the embodiment of the present invention, it is possible to adaptably select the down-link relay route even in the case where the terminal station has moved. The shorter a transmission cycle of the broadcast packet is, the faster move of the terminal station can be the subject of implementation of the down-link relay route selection.

10 In addition, a radio relay type cellular network as a precondition has the effect of allowing more stable communication compared with an ad hoc network wherein a moving terminal serves concurrently as the relay center, since the relay nodes are deployed fixedly as infrastructure.

15 Moreover, it is feasible, by controlling the transmitting power of an up-link data packet or a down-link data packet, to cut back interference given to the surrounding nodes and terminal stations, whereby it consequently has the effect of allowing the link capacity in the entire system to be improved.

20 FIG. 12 is a flowchart showing another example of the up-link ACK packet procedure performed on each relay node and core node according to the embodiment of the present invention. As shown in FIG. 12, each node detects arrival of the up-link ACK packet in a step D01, and it proceeds to a step D02 in the case where the up-link ACK packet is detected, and it returns to the step D01 in the case where the up-link ACK packet is not detected. In the step D02, each node determines whether the received up-link ACK packet is the packet being relayed or the packet transmitted

from the terminal station. Here, the determination is made by referring to the field G03 representing the relay source node included in the ACK packet, and if information set in the field G03 indicates anything other than the relay source node, each
5 node determines that the received up-link ACK packet is the packet from the terminal station. In the case where it is determined to be the up-link ACK packet from the terminal station in the step D02, each node transmits the up-link ACK packet to the relay destination node after setting necessary information such as
10 the relay source node ID in a step D06. In the case where the terminal station or the relay node transmits the up-link ACK packet, it may control the transmitting power of the up-link ACK packet so as to meet predetermined received power or
predetermined received quality at the transmission destination
15 node. It is possible to cut back the interference and increase the link capacity by controlling the transmitting power of the up-link ACK packet.

In the case where it is determined to be the up-link ACK packet from the relay source node in the step D02, each node
20 refers to the relay destination node ID included in the up-link ACK packet in a step D03, and it proceeds to a step D04 if its own node ID is set in the field G02, or returns to the step D01 if anything other than its own node ID is set in the field G02. In the step D04, each node obtains the information on the relay
25 source node ID and the source terminal station ID included in the received up-link ACK packet, and determines whether or not their relationship is already recorded with the relay node list. In the case where, in the step D04, it is determined that the

pair of the relay source node ID and the source terminal station ID included in the received up-link ACK packet is already registered, each node does not relay the packet and returns to the step D01. In the case where it is not registered, each node registers the relationship between the relay source node ID and the source terminal station ID with the relay node list in a step D05. Here, in the case where the above described source terminal station ID is already registered with the relay node list, each node cancels the registration thereof and then registers the pair of the relay source node ID and the source terminal station ID of this time. After registering it with the relay node list in the step D05, each node transmits the up-link ACK packet to the relay destination node after setting the necessary information such as the relay source node ID in the step D06.

FIG. 13 is a diagram concretely illustrating how the relay node list is generated according to the up-link ACK packet procedure shown in FIG. 12. In FIG. 13, placement of the terminal stations and relay nodes equal to that in FIG. 6 is assumed, and it represents a situation where the terminal stations MS-A, MS-B, MS-D and MS-C transmit or relay and transmit the up-link ACK packets to the relay nodes RN-1, RN-2, RN-3, RN-4 and RN-5 respectively, and then the terminal station MS-B receives the broadcast packet to transmit the up-link ACK packet again. In FIG. 13, the terminal station MS-B receives the broadcast packet from the relay node RN-2 by way of the radio propagation path I09, and selects the relay node RN-2 as the connection node. The terminal station MS-B transmits the up-link ACK packet to

the relay node RN-2 by way of the radio propagation path I08. At this time, the up-link ACK packet has the ID "MS-B" set as the source terminal station ID and the ID "RN-2" set as the relay destination node ID respectively. The relay node RN-2 receives
5 the up-link ACK packet transmitted from the terminal station MS-B, and then transmits the up-link ACK packet to the relay node RN-3 that is the up-link relay destination node for the relay node RN-2 by way of the radio propagation path I05. At this time, the up-link ACK packet has the ID "RN-2" set as the
10 relay source node ID, the ID "MS-B" set as the source terminal station ID and the ID "RN-3" set as the relay destination node ID respectively. The relay node RN-3 refers to the relay source node ID "RN-2" and the source terminal station ID "MS-B" included in the up-link ACK packet transmitted from the relay node RN-2
15 to check whether or not the pair of the node ID "RN-2" and the terminal station ID "MS-B" is already registered with the relay node list held by the relay node RN-3.

As shown in FIG. 8, the pair of the ID "RN-2" and the ID "MS-B" is already registered with the relay node list held by the relay
20 node RN-3. And according to this example of relay node list generation, in the case where, as shown in FIG. 12, the pair of the relay source node ID and the source terminal station ID included in the relayed and transmitted up-link ACK packet is already registered with the relay node list, the relay node RN-3
25 does not relay and transmit the up-link ACK packet to the relay node (relay node RN-4) of higher order. Thus, it becomes possible to transmit the up-link ACK packet only in the case where the relay route needs to be changed, and traffic for transmitting

the up-link ACK packet can be reduced, thus allowing the interference to be cut back and the link capacity in the entire system to be improved.

Moreover, when generating the relay node list in the embodiment of the present invention, it is also possible to generate the relay node list with the up-link packets other than the up-link ACK packet. Here, the up-link packets refer to up-link data packets transmitted by the terminal station, which are transmitted none the less whether or not the broadcast packet is received.

FIG. 14 is a schematic diagram showing the configuration of the up-link packet. In FIG. 14, the up-link packet is comprised of a field 502 showing the relay destination node ID, a field 503 showing the relay source node ID, a field 504 showing the source terminal station ID and the other field 501. In the relay node, the up-link relay destination node ID is set as the relay destination node ID, its own node ID is set as the relay source node ID, and the ID of the terminal station having transmitted the up-link packet is set as the source terminal station ID. In the case where the terminal station transmits the up-link packet, the terminal station sets the information, as the relay source node ID, indicating that the packet was transmitted by the station. It is also possible to simultaneously set a plurality of the relay destination node IDs in the field 502. The other field 501 has a pilot, an up-link and down-link indicator, a packet ID, data and so on set. The order of the fields may change. The other field 501 may be divided and placed.

In FIGS. 4 and 12 showing the ACK packet procedure respectively, the relay node list is generated by replacing the portion equivalent to the up-link ACK packet with the up-link packet shown in FIG. 14.

5 Next, the down-link packet relay and transmission method according to the embodiment of the present invention will be described. FIG. 15 is a schematic diagram showing the field configuration of the down-link packet. In FIG. 15, the down-link packet is comprised of a field 602 showing the relay destination
10 node ID, a field 603 showing the relay source node ID, a field 604 showing the destination terminal station ID and the other field 601. In the case where a certain relay node relays and transmits the down-link packet, the relay node determines the relay destination node ID corresponding to the destination
15 terminal station ID from the relay node list, and then sets the relay destination node ID in the relay destination node ID field 602, sets the destination terminal station ID in the destination terminal station ID field 604, and sets the node ID of the relay node in the relay source node ID field 603. In the case where
20 a certain relay node transmits the down-link packet directly to the terminal station, the relay node sets the information dedicated to indication thereof in the relay destination node ID field 602. The other field 601 has a pilot, an up-link and down-link link indicator, a packet ID, data and so on stored.
25 The order of the fields may change. The other field 601 may be divided and placed.

FIG. 16 is a flowchart showing the relay transmission process of the down-link packet shown in FIG. 15, and this process is

one executed on the core node and the relay node. In FIG.16,
each node detects arrival of the down-link packet in a step S701,
and it proceeds to a step S702 if the down-link packet arrives,
and it returns to the step 701 if the arrival of the packet is
5 not detected. In the step S702, each node determines whether
or not the relay destination node ID included in the down-link
packet is its own node ID, and if its own node ID is set in the
field 602, it proceeds to a step S706, and if not, it returns
to the step S701. In the step S706, each node checks the
10 destination terminal station ID indicating the destination of
the down-link packet, and determines whether or not the
destination terminal station ID is included in the relay node
list. In the case where the destination terminal station ID
is included in the relay node list, it proceeds to a step S703,
15 and if the ID is not included therein, it proceeds to a step
S705. In the step S703, each node selects from the relay node
list the node ID to pair off with the destination terminal station,
sets the node ID as the relay destination node ID on the down-link
packet. In a step 704, each node transmits the down-link packet
20 to the relay destination node selected in the step S703. Here,
the down-link packet to be relayed and transmitted has its own
node ID set as the relay source node ID and also has the destination
terminal station ID and the relayed data and so on set respectively.
When the core node or the relay node transmits the down-link
25 packet, it may control the transmitting power of the down-link
packet so as to meet predetermined received power or predetermined
received quality at a transmission destination node or terminal
station. It is possible, by controlling the transmitting power

of the down-link packet, to cut back the interference given to the surroundings, whereby allowing high link utilization to be attained.

On the other hand, in the case where the destination terminal station ID is not included in the relay node list in the step S706, each node transmits the down-link packet directly to the terminal station in a step S705. At this time, the down-link packet has its own node ID set as the relay source node ID and also has the information indicating that the down-link packet is transmitted to the terminal station set in the relay destination node ID field 602. In addition, the down-link packet has the destination terminal station ID, the down-link data and so on set respectively.

FIG. 17 is a diagram concretely illustrating the down-link packet relay operation by the down-link packet relay transmission shown in FIG. 16. In FIG. 17, placement of the terminal stations and relay nodes that is the same as FIG. 6 is assumed, and the relay node lists to the terminal stations MS-A, MS-B, MS-C and MS-D are already generated on the relay nodes RN-1, RN-2, RN-3 and RN-4. Now, the down-link packet sent to the terminal station MS-B arrives at the relay node RN-4. The relay node RN-4 refers to the relay node list shown in FIG. 9, and it grasps that the relay destination node to pair off with the terminal station MS-B is the relay node RN-3. The relay node RN-4 relays the down-link packet to the relay node RN-3. Here, the relay node RN-4 sets the ID "RN-4" as the relay source node ID, sets the ID "RN-3" as the relay destination node ID, and sets the ID "MS-B" as the destination terminal station ID on the down-link packet

to be relayed. In addition, the other information (transmission data or the like) included in the down-link packet sent to the terminal station MS-B having arrived at the relay node RN-4 is also set on the down-link packet. After the relay node RN-4
5 transmits the down-link packet to the relay node RN-3 by way of a radio propagation path 301, the relay node RN-3 receives the down-link packet. The relay node RN-3 checks the destination terminal station of the down-link packet transmitted from the relay node RN-4, and checks whether or not the terminal station
10 is included in the relay node list held by the relay node RN-3 shown in FIG. 8. As the terminal station MS-B pairs off with the relay node RN-2 as shown in FIG. 8, the relay node RN-3 transmits the down-link packet to the relay node RN-2 just as in the case where the relay node RN-4 relayed and transmitted the down-link
15 packet to the relay node RN-3. The relay node RN-2 likewise checks whether or not the terminal station MS-B is registered with the relay node list held by the relay node RN-2 shown in FIG. 7. As the ID "MS-B" that is the ID of the destination terminal station MS-B is not registered with the relay node list held
20 by the relay node RN-2 as shown in FIG. 7, the relay node RN-2 determines that the terminal station MS-B belongs to the area of its own node, and transmits the down-link packet to the terminal station MS-B. At this time, on the down-link packet to be sent to the terminal station MS-B, the relay node RN-2 sets the ID "RN-2"
25 as the relay source node ID, sets the information dedicated to the indication of transmission to the terminal station in the relay destination node ID field 602, and sets the ID "MS-B" as the destination terminal station ID. In addition, the relay

node RN-2 also sets a data signal or the like included in the down-link packet received by the relay node RN-2 on the down-link packet as appropriate.

5 The terminal station MS-B receives the down-link packet from the relay node RN-2, confirms that it is the packet sent to its own terminal and then demodulates the data.

As above, according to the embodiment of the present invention, it is possible to adaptably select the down-link relay route even in the case where the terminal station has moved.
10 The shorter the transmission cycle of the broadcast packet is, the faster move of the terminal station can be the subject of implementation of the down-link relay route selection.

In addition, a radio relay type cellular network as a precondition has the effect of allowing more stable communication
15 compared with the ad hoc network wherein the moving terminal serves concurrently as the relay center, since the relay nodes are deployed fixedly as infrastructure.

Moreover, it is feasible, by controlling the sending power of the up-link data packet or the down-link data packet, to cut
20 back interference given to the surrounding nodes and terminal stations, whereby it consequently has the effect of allowing the link capacity in the entire system to be improved.

According to the present invention, the information on the relay route of the up-link packet is held as the relay node list
25 on the core node and the relay node, and the relay route of the down-link packet is selected based on the above described information recorded on the relay node list, so that it has the advantage of allowing selection of the appropriate down-link

relay route according to the location of the terminal and further allowing selection of the down-link relay route to be autonomously implemented in each of the relay nodes.

In addition, the present invention has the effect that,
5 in the case where the terminal station moves, the relay route of the down-link packet to the terminal station can be changed as appropriate following the move.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2